

adjusting the power of the lamp for overtemperature protection, display panel real-time view of the working temperature of the lamp

Control mode: DMX wired. Wireless signal optional/manual control

Protection level: IP20

Fittings: Shutter, power cord, signal cable


Net weight/gross weight: 8kg

Lamp body size: 615*280*215MM

400W LED Fresnel Spot Light



User Manual

 Please read this user manual before using this product!

Keep it for further reference!

| | | | | | |
|---|--------------|-----|---|-----|--------------------------|
| 2 | Dimmer1 | 0 | - | 255 | Dimmer 1 |
| 3 | Dimmer2 | 0 | - | 255 | Dimmer 2 |
| 4 | Dimmer3 | 0 | - | 255 | Dimmer 3 |
| 5 | Dimmer4 | 0 | - | 255 | Dimmer 4 |
| 6 | Dimmer5 | 0 | - | 255 | Dimmer 5 |
| 7 | Zoom | 0 | - | 255 | Zoom |
| 8 | Strobe | 0 | - | 4 | No strobe |
| | | 5 | - | 255 | Strobe from slow to fast |
| | | 0 | - | 9 | No Function |
| | | 10 | - | 19 | Preset Color 1 |
| | | 20 | - | 29 | Preset Color 2 |
| | | 30 | - | 39 | Preset Color 3 |
| | | 40 | - | 49 | Preset Color 4 |
| | | 50 | - | 59 | Preset Color 5 |
| | | 60 | - | 69 | Preset Color 6 |
| | | 70 | - | 79 | Preset Color 7 |
| | | 80 | - | 89 | Preset Color 8 |
| | | 90 | - | 99 | Preset Color 9 |
| | | 100 | - | 109 | Preset Color 10 |
| | | 110 | - | 119 | Preset Color 11 |
| | | 120 | - | 129 | Preset Color 12 |
| | | 130 | - | 139 | Preset Color 13 |
| | | 140 | - | 149 | Preset Color 14 |
| | | 150 | - | 159 | Preset Color 15 |
| | | 160 | - | 169 | Preset Color 16 |
| | | 170 | - | 179 | Preset Color 17 |
| | | 180 | - | 189 | Preset Color 18 |
| | | 190 | - | 199 | Preset Color 19 |
| | | 200 | - | 209 | Preset Color 20 |
| | | 210 | - | 219 | Preset Color 21 |
| | | 220 | - | 229 | Preset Color 22 |
| | | 230 | - | 239 | Preset Color 23 |
| 9 | Preset Color | | | | |

| | | | | | |
|----|------------|-----|---|-----|--------------------|
| | | 240 | - | 249 | Preset Color 24 |
| | | 250 | - | 255 | Preset Color 25 |
| | | 0 | - | 4 | No Function |
| | | 5 | - | 100 | Skip |
| 10 | Macro Func | 101 | - | 200 | Slip |
| | | 201 | - | 255 | Audio |
| 11 | Speed | 0 | - | 255 | Skip or Slip speed |

Note: When using DMX512 mode, do not have a light set to the host voice control stroboscopic mode otherwise it will interfere with each other. After power, press the knob to display 001 indicates that it is in DMX512 mode, and other characters are not in 512 mode

Technical parameters:

Light source: RGBAL 5-in-1 high display LED lamp bead

Supply voltage: AC100~240V, 50/60Hz

Rated power: 400W

Light source life: up to 50,000 hours

Color system: RGBAL color mixing system and rainbow effect

Effect configuration: 0-100% linear dimming, 4 dimming curves and 4 dimming frequency options

Fast stroboscopic: 1 to 25Hz

2500K-10000K color temperature linear adjustment

Color macro with color gradient effect

Channel mode: 7CH/11CH

Control panel: LCD display + four buttons

Optics: 15-60 degrees linear manual zoom, 24K flicker-free light source management system, no glare and glare

Heat dissipation mode: Fan heat dissipation

Temperature monitoring: Built-in temperature protection sensor, by automatically